

Logic design (Fall 2018)

Quiz # 1

Name: _____ ID: _____

1. (30%+20%) Convert 163.5_7 to binary and then to hexadecimal.

Hint: convert binary to hexadecimal by inspection.

Ans:

$$163.5_7 = 1 \times 7^2 + 6 \times 7^1 + 3 \times 7^0 + 5 \times 7^{(-1)} = 49 + 42 + 3 + 5/7 = 94 \frac{5}{7}_{10}$$

$$\frac{94}{2} = 47 \dots 0 \Rightarrow \frac{47}{2} = 23 \dots 1 \Rightarrow \frac{23}{2} = 11 \dots 1 \Rightarrow \frac{11}{2} = 5 \dots 1$$

$$\Rightarrow \frac{5}{2} = 2 \dots 1 \Rightarrow \frac{2}{2} = 1 \dots 0 \Rightarrow \frac{1}{2} = 0 \dots 1$$

$$5/7 \times 2 = 1 \frac{3}{7} \Rightarrow 3/7 \times 2 = \frac{6}{7} \Rightarrow 6/7 \times 2 = 1 \frac{5}{7} \Rightarrow 5/7 \times 2 = 1 \frac{3}{7} \Rightarrow \dots$$

$$163.5_7 = 1011110.\underline{101}_2 = 0101 \ 1110.\underline{1011 \ 0110 \ 1101}_2 = 5E.\underline{B6D}_{16}$$

2. (30%) Represent -11_{10} and 4_{10} as two 5-bit 1's complement numbers, denoted by a and b , respectively. Calculate $a - b$ by adding the complement of b to a . Indicate whether an overflow occurs. Hint: $a - b = a + (-b)$

Ans:

$$a = 10100, \quad b = 00100$$

$$\begin{array}{r} 10100 \\ + \underline{11011} \\ (1)01111 \\ \hline \quad \quad \quad \underline{1} \\ 10000 \end{array}$$

No overflow

3. (20%) Represent 247 in excess-3 code.

Ans:

$$0101 \ 0111 \ 1010$$

$$(2) \ (4) \ (7)$$